

## DS-PM1-I16O2-WE Multi IO Transmitter



DS-PM1-I16O2-WE wireless multi IO transmitter offers a connection of third party wired detectors like outdoor PIR, to AX PRO alarm system, the alarm types and zone parameters can be set through APP by installers easily. Under the situation when your want to update your security system to AXPRO with more innovated features, multi IO transmitter gives you a chance to rebuild your alarm system without changing existing wired detectors.

- 868 MHz two-way wireless communication
- LED display, show the real status of device
- With 16 onboard inputs and 2 outputs, can be applied to connect wired detectors
- With two 12 V power outputs, can be used to power up external wired detectors
- Large space for back up storage battery



## ▪ Specification

Software features	
End of Line Resistance	1k 2.2k 4.7k 8.2k NO/NC
Hardware features	
Serial port	1
Battery port	1, 12 VDC input
Tamper-Proof	Front and rear
Power switch	1
Alarm input	16
Alarm output	2
Power Output	2 (12 V, total1 A)
Electrical characteristics	
Battery type	Compatible with 12 V 7 Ah 150 × 64 × 94 mm
Power supply	100-240 VAC, 30 W
Operation humidity	10% to 90%
Operation temperature	-10 to 40°C
Power consumption	Battery Supply: Quiescent current (50 mA), Max current (1500 mA), Voltage (13.8 V) 220 V Supply: Quiescent current (45 mA), Max current (300 mA), Voltage (220 V)
Battery life span	Up to 36 hours
Wireless transmission	
RF frequency	868 MHz
RF method	Two-way communication
RF modulation	2GFSK
RF distance	1100 m
Display	
Indicator	3: Power(Green), Fault(Amber), Signal Strength(Green/Red)
General	
Installation method	Wall Mounting
Dimension(W × H × D)	261 × 199 × 86.4 mm
Shell material	Plastic
Color	White
Weight	975 g (without battery)

## ▪ Available Model

DS-PM1-I1602-WE

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
Info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7852-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-97-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com